

# SITE-ARC

## GPH & GPV (PETROL) GENERATORS



MODEL:	GPH 6.5 / 1 - CR	GPH 8.0 / 1 - AVR	GPV 11.0 / 1 - AVR	GPV 13.5 / 3 - AVR
ENGINE:	HONDA GX390	HONDA GX390	VANGUARD 23HP - EFI	VANGUARD 23HP - EFI
FUEL:	PETROL	PETROL	PETROL	PETROL
GENERATOR:	6.5kVA - 1 Phase	8.0kVA - 1 Phase	11.0kVA - 1 Phase	13.5kVA - 3 Phase
VOLTAGE:	110 / 230 V	110 / 230 V	110 / 230 V	230 / 400 V
MAX AMPS:	59 / 28 A	70 / 34 A	100 / 47 A	20A 3ph, 16A 1 ph
PROTECTION:	CIRCUIT BREAKER	CIRCUIT BREAKER	CIRCUIT BREAKER	CIRCUIT BREAKER
SOCKETS:	1x16, 1x32 110/230	2x16, 1x32 110/230	1x16, 1x32, 110/230 1x 63-230	1x32-400, 1x 16-230
FULL FRAME:	INC 4 WHEEL TROLLEY	INC 4 WHEEL TROLLEY	INC 4 WHEEL TROLLEY	INC 4 WHEEL TROLLEY
DIMENSIONS:	L:1000 / W:620 / H:700mm	L:1000 / W:620 / H:700mm	L:1200 / W:700 / H:825mm	L:1200 / W:700 / H:825mm
WEIGHT (DRY):	109KG	119KG	130KG	145KG
SOUND LEVEL:	95dba	95dba	93dba	93dba

